



CoolJag Everflow 60x25mm PWM Fan with Two Ball Bearings - 6800RPM

\$9.95

Product Images



Short Description

CoolJag Everflow 60x25mm PWM Fan with Two Ball Bearings - 6800RPM

Description

CoolJag Everflow 60x25mm PWM Fan with Two Ball Bearings - 6800RPM

Specifications

- Fan size: 60x60x25mm
- Fan voltage: 12V
- Bearing: Dual Ball bearing
- Fan speed: 1300 ~6800 rpm
- Noise Level: 18 ~41 dBA
- Air Flow: 6.5 ~34 CFM
- Power : 1.2 ~3.12 W
- Static pressure : 0.38 ~10.36 mmH2O
- Fan connector: 4-pin
- Lead wire: UL1430 #26AWG or equivalent
- Pin Assignment : Pin 1 Black (GND), Pin 2 Yellow (PWR), Pin 3 Green (SGN), Pin 4 Blue (PWM)

Additional Information

Brand	CoolJag
SKU	F126025BUAF-6800
Weight	0.2500
Color	Black
Fan Dimensions	60mm
Fan Width	25mm
Fan Connection	4-Pin PWM
Fan Voltage	12 VDC
Fan RPM	6800
Fan CFM	34
Fan Noise (dB)	41

