



Scythe KM06-BK Kaze Master Flat 4 Channel 5.25in Bay Fan Controller - Black

Special Price
\$29.00 was
\$45.95

Product Images





Short Description

The Kaze Master Flat is a fan control unit featuring some neat original functions making it a little different from the competition: It's equipped with four channels for rpm and temperature display and is designed to fit into the 5.25 bay. Fitted with a modern front panel, an alarm function and a hinged display cover for protection, the package is rounded up with jumper switches for individual settings by the user. Even with closed cover, the displays of the LCD-panel are discreetly visible through the integrated window.

Description

The Kaze Master Flat is a fan control unit featuring some neat original functions making it a little different from the competition: It's equipped with four channels for rpm and temperature display and is designed to fit into the 5.25 bay. Fitted with a modern front panel, an alarm function and a hinged display cover for protection, the package is rounded up with jumper switches for individual settings by the user. Even with closed cover, the displays of the LCD-panel are discreetly visible through the integrated window.

Features

- Liquid Crystal Display
The Kaze Master Flat's discreet LCD-display provides the user with information about the temperature and the rpms for each of the four fans. It's neatly arranged and can be switched off at the user's convenience. **Display is blue in color.**
- Protective Display Cover

The front panel of the Kaze Master Flat protects its' display with a hinged cover which also prevents unintentionally touching the switches. The information displayed is clearly visible through the integrated window even in closed state.

- Spin Up Voltage

The adjustable voltage range is between 3.7 to 12 volts. But as fans tend to have problems to "get going" in the lower ranges, this function ensures a 12 volt supply right from the start before settling down to the user`s set, desired voltage.

- Temperature Warning Function

By applying the dip-switch, the user is able to set the desired temperature for the alarm to go off. The values can be set between 55 (131 F) and 90 degrees (194 F) in 5-degree steps.

- Jumper Switch for Personal Settings

For personal settings by each individual user, the Kaze Master Flat comes with two jumper switches - one for turning the alarm sound on/off, the other one for choosing between Celsius and Fahrenheit.

Specifications

Model Name:

Kaze Master Flat

Model-No.:

KM06-BK (Black)

Overall Dimensions (W x H x D):

148,5 x 42 x 83 mm / 5.8 x 1.6 x 3.26 in

Display Dimensions (W x H):

119.3 x 16 mm / 4.7 x 0.62 in

DC Input:

5 V or 12 V (From PC Power Supply)

DC Output:

3,7 V ($\pm 10\%$) ~ 12 V ($\pm 10\%$)

Fan Channels:

4

Fan Speed Range:

0 - 9990 upm

Temperature Channels:

4 (0 - 100°C / 32 - 199,9°F)

Weight:

160 g

Accessory:

4x Temperature Sensor Cables, 4x Fan Cables, 1x Power Cable, 4x Mounting Screws, Installation Manual

Additional Information

Brand	Scythe
SKU	KM06-BK
Weight	2.0000
Color	Black
Device Type	Fan Controller
Bay Size	5.25" Bay
Vendor SKU/EAN	894092004400
Special Price	\$29.00

